PINTEK Differential Probe

★ 16 KV High Voltage !
★ 100 mV Sensitivity !

DP-16K/16KM/16KL

100 MHz,70MHz,50MHz /16KVp-p

- High Frequency Performance Model
- Bandwidth:(-3 dB)
  DC～100 MHz (DP-16K)
  DC～70 MHz (DP-16KM)
  DC～50 MHz (DP-16KL)
- 2 Range: x100, x1000
- Input Impedance:
  10 MΩ // 10 pF each side to ground
- Over Range Indicate LED
- Rise Time: 4 ns

APPLICATIONS:

- High Speed Switching Mode Power Supply Design.
- Research and Development.
- High Speed Motor Development.
- Manufacturing Engineering Test.
- Digital Design and Characterization.

CE

Pintek Electronics Co., Ltd
www.pintek.com.tw